

OPTIONAL RAM

The expansion RAM chip (Cat.No. 26-2853) expands the printer's temporary memory to 40K bytes (internal 8K plus an additional 32K). Take your printer to a Radio Shack Service Center to have the chip installed. Installation MUST be done by Service Center.

Menu Options:

The OPTN RAM Group appears only when you define macros with the optional RAM chip installed. Press SELECT when the SPECIAL/SET? message appears after the CHR TABLE menu group. The settings in this menu are common to all four macros.

The setup menu option will display on the LCD as follows:

Group	Item	Set
SPECIAL	OPTN RAM	BUFFER, DOWNLOAD

Note: BUFFER is the default mode.

The optional RAM can be used in one of two ways for the IBM emulation of the DMP-240. The additional 32-K byte RAM area can be used as an additional receive buffer (BUFFER), or an IBM font download area (DOWNLOAD).

The Epson mode of the printer will only allow the optional ram to be used as an additional receive buffer (BUFFER). If (DOWNLOAD) is selected, the optional RAM area is disabled.

(css 07/27/93)