

3000 E (250-4002)

Memory

Faxback Doc. # 1033

256K DRAM Kits -

250-1079 consists of eight 256K X 1 DRAMS at 150 nanoseconds.

√250-3062 consists of eight 256K X 1 DRAMS at 150 nanoseconds and one parity chip. The individual chips can be ordered from Tandy National parts under cat # 250-4030, part # MX-6796 (order 9 for a complete 250-3062 or one to complete a 250-1079..

Memory Boards -

√250-4030 is a 16-bit, 0 K Memory Expansion Board. This product can be obtained from Tandy National Parts under cat # 250-4030, part # AX-0104. The AX-0104 has 512K of RAM already installed.

Third Party - Memory expansion can also be accomplished by using third party 16- bit memory board.

√ = Discontinued Radio Shack product

Tandy 3000/E (250-4002) - Expand from 640K:		
	Memory Adapter	Add to Memory Adapter
1.5MB	AX-0104	N/A
2MB	AX-0104	(2) 250-1079 & (2) MX-6796
2.5MB	AX-0104	(4) 250-1079 & (4) MX-6796
3MB	AX-0104	(6) 250-1079 & (6) MX-6796
Beyond 3MB	To increase beyond 3MB, use additional AX-0104 boards and memory kits.	

RAM Shipped With 640K Max Extended RAM 12 MB

(Maximum Extended RAM is 14 MB if a hard drive controller is NOT included in the system.)

(smm 08/06/93)