

This Joystick adapter connects a standard Tandy 6-pin DIN joystick to the new 8-pin Mini DIN connector used on some units. This adapter is used on the 1000 RLX (version B) computer, and the Tandy Multimedia boards (25-1085 and 25-1090).

Use the adapter for a Tandy joystick like the Pistol Grip Joystick (26-3123)

Below are the pinouts for adapter:

8-pin Mini DIN (Male)	Signal Descriptions	6-pin DIN (Female)
1	X Position	1
2	Y Position	2
3	Ground	3
4	N/C	
5	Power +5V	5
6	Ground	
7	Button #1	4
8	Button #2	6

(rjs-06/25/93)